

Optus Settings:

Access Point	Optus- Internet	Optus – MMS
Name	Optus Yes Internet	Optus MMS
APN	yesinternet	mms
Proxy	<not set>	<not set>
Port	<not set>	<not set>
Username	<not set>	<not set>
Password	<not set>	<not set>
Server	<not set>	<not set>
MMSC	<not set>	http://mmsc.optus.com.au:8002/
MMS Proxy	<not set>	61.88.190.10
MMS Port	<not set>	8070
MMS Protocol (Android 2.1+)	WAP 2.0	WAP 2.0
MCC	505	505
MNC	02	02
Auth Type	None	None
APN Type	default	mms

Telstra Settings:

Access Point	Telstra – Internet	Telstra – MMS
Name	Telstra Internet	Telstra MMS
APN	telstra.iph	telstra.mms
Proxy	<not set>	<not set>
Port	<not set>	<not set>
Username	<not set>	<not set>
Password	<not set>	<not set>
Server	wap.telstra.com/wap	<not set>
MMSC	<not set>	http://mmsc.telstra.com:8002
MMS Proxy	<not set>	10.1.1.180
MMS Port	<not set>	80
MMS Protocol (Android 2.1+)	WAP 2.0	WAP 2.0
MCC	505	505
MNC	01	01
Auth Type	CHAP	CHAP
APN Type	default	mms

Vodafone Settings:

Access Point	Vodafone – Internet Access	Vodafone AU-MMS
Name	VF WEB	VF PXT
APN	<not set>	live.vodafone.com
Proxy	<not set>	<not set>
Port	8080	<not set>
Username	<not set>	<not set>
Password	<not set>	<not set>
Server	<not set>	<not set>
MMSC	http://pxt.vodafone.net.au/pxtsend	http://pxt.vodafone.net.au/pxtsend
MMS Proxy	10.202.2.060	10.202.2.060
MMS Port	8080	8080
MMS Protocol (Android 2.1+)	<not set>	<not set>
MCC	505	<not set>
MNC	03	<not set>
Auth Type	PAP	PAP
APN Type	default	mms

Three (3) Settings:

Access Point	Three (3) – Internet Access	Three (3) – MMS
Name	3 Services	3MMS
APN	3services	3services
Proxy	<not set>	<not set>
Port	<not set>	<not set>
Username	<not set>	<not set>
Password	<not set>	<not set>
Server	<not set>	<not set>
MMSC	<not set>	http://mmsc.three.net.au:10021/mmsc
MMS Proxy	<not set>	10.176.57.25
MMS Port	<not set>	8799.00
MMS Protocol (Android 2.1+)		<not set>
MCC	<not set>	<not set>
MNC	<not set>	<not set>
Auth Type	<not set>	<not set>
APN Type	default	mms

Virgin Settings:

Access Point		Virgin – Internet & MMS
Name	Virgin Internet	
APN	VirginInternet	
Proxy	202.139.83.152	
Port	8070	
Username	<not set>	
Password	<not set>	
Server	<not set>	
MMSC	http://mms.virginvibe.com.au:8002/	
MMS Proxy	202.139.83.152	
MMS Port	8070	
MMS Protocol (Android 2.1+)	<not set>	
MCC	505	
MNC	02	
Auth Type	<not set>	
APN Type	default	

Amaysim:

Access Point		amaysim – Internet	amaysim – MMS
Name	Amaysim		Optus MMS
APN	Internet		mms
Proxy	<not set>		<not set>
Port	<not set>		<not set>
Username	<not set>		<not set>
Password	<not set>		<not set>
Server	<not set>		<not set>
MMSC	<not set>		http://mmsc.optus.com.au:8002/
MMS Proxy	<not set>		66.88.190.10
MMS Port	<not set>		8070
MMS Protocol (Android 2.1+)	<not set>		<not set>
MCC	505		505
MNC	02		02
Auth Type	PAP		PAP
APN Type	default		MMS

Crazy John's Settings:

Access Point	Crazy John's – Internet	Crazy John's – MMS
Name	Crazy NET	Crazy MMS
APN	purtona.net	purtona.wap
Proxy	<not set>	010.202.002.020
Port	<not set>	8080
Username	<not set>	<not set>
Password	<not set>	<not set>
Server	<not set>	<not set>
MMSC	<not set>	http://purtona.mms/mmssend
MMS Proxy	<not set>	010.202.002.020
MMS Port	<not set>	8080
MMS Protocol (Android 2.1+)	<not set>	<not set>
MCC	505	505
MNC	03	03
Auth Type	<not set>	<not set>
APN Type	default	mms

TPG Settings:

Access Point	TPG Mobile – Internet	TPG Mobile – MMS
Name	TPG Internet	Optus MMS
APN	internet	mms
Proxy	203.139.83.152	<not set>
Port	8070	<not set>
Username	<not set>	<not set>
Password	<not set>	<not set>
Server	<not set>	<not set>
MMSC	<not set>	http://mmsc.optus.com.au:8002/
MMS Proxy	<not set>	61.88.190.10
MMS Port	<not set>	8070
MMS Protocol (Android 2.1+)	<not set>	WAP 2.0
MCC	505	<not set>
MNC	02	<not set>
Auth Type	<not set>	<not set>
APN Type	default	mms

Dodo Settings:

Access Point	Dodo- Internet	Dodo – MMS
Name	Internet	MMS
APN	Internet	mms
Proxy	202.139.83.152	61.88.190.10
Port	9201	9201
Username	<not set>	<not set>
Password	<not set>	<not set>
Server	http://networker.optus.net.au/wap/index.wml	<not set>
MMSC	<not set>	http://mmsc.optus.com.au:8002/
MMS Proxy	<not set>	61.88.190.10
MMS Port	<not set>	9201
MMS Protocol (Android 2.1+)	WAP 2.0	WAP 2.0
MCC	505	505
MNC	02	02
Auth Type	PAP	PAP
APN Type	default	mms

iinet Settings:

Access Point	iinet- Internet	iinet – MMS
Name	iinet Internet	Optus MMS
APN	internet	mms
Proxy	<not set>	<not set>
Port	<not set>	<not set>
Username	<not set>	<not set>
Password	<not set>	<not set>
Server	<not set>	<not set>
MMSC	<not set>	http://mmsc.optus.com.au:8002/
MMS Proxy	<not set>	61.88.190.10
MMS Port	<not set>	8070
MMS Protocol (Android 2.1+)	WAP 2.0	WAP 2.0
MCC	505	505
MNC	02	02
Auth Type	<not set>	<not set>
APN Type	internet	mms

ALDI mobile Settings:

Access Point	ALDI mobile - Internet	ALDI mobile - MMS
Name	Mobile Data	Mobile Data
APN	mdata.net.au	mdata.net.au
Proxy	<not set>	<not set>
Port	<not set>	<not set>
Username	<not set>	<not set>
Password	<not set>	<not set>
Server	<not set>	<not set>
MMSC	<not set>	http://mmsc.mdata.net.au:8003
MMS Proxy	<not set>	10.1.1.180
MMS Port	<not set>	80
MMS Protocol (Android 2.1+)	WAP 2.0	WAP 2.0
MCC	505	505
MNC	01	01
Auth Type	<not set>	<not set>
APN Type	default	mms